

CONNECTOR LAYOUTM460T INPUT MODULE

		P1			
MIC	A	1	MIC		
NC	B	2	MIC SHIELD		
RS1	C	3	RS1		
FB2	D	4	FB2		
FB1	E	5	FB1		
AUX4	F	6	AUX4		
AUX3	H	7	AUX3		
AUX2	J	8	AUX2		
AUX1	K	9	AUX1		
PFL	L	10	PFL		
NC	M	11	NC		
SOLO	N	12	SOLO		
NC	P	13	NC		
NC	R	14	NC		
NC	S	15	NC		
ATT IN SHIELD TIE	T	16	ATT IN SHIELD TIE		
LINE IN	U	17	LINE IN		
ATT OUT SHIELD TIE	V	18	ATT OUT SHIELD TIE		
BOOSTER IN	W	19	BOOSTER IN		
CH ON OUT	X	20	CH ON OUT		
CH ON IN	Y	21	CH ON IN		
PRE OUT	Z	22	PRE OUT		

LEGEND:

NC: NOT CONNECTED

IC: INTERNALLY CONNECTED

(UPPER)

CONNECTOR LAYOUTM460T INPUT MODULE

		P2			
NC	A	1	NC		
GND	B	2	GND		
LEFT OUT	C	3	LEFT OUT		
IC	D	4	IC		
RIGHT OUT	E	5	RIGHT OUT		
IC	F	6	IC		
GND	H	7	GND		
IC	J	8	IC		
NC	K	9	NC		
IC	L	10	IC		
IC	M	11	IC		
DIRECT	N	12	DIRECT		
IC	P	13	IC		
IC	R	14	IC		
NC	S	15	IC		
RS CONTROL	T	16	PFL CONTROL		
MUTE CONTROL	U	17	MUTE CONTROL		
SOLO CONTROL	V	18	CONTROL COM.		
CH ON	W	19	-25V		
25V COM.	X	20	25V COM.		
+24V	Y	21	+25V		
CH ON LAMP	Z	22	CHASSIS		

LEGEND: CH ON LAMP  
 NC: NOT CONNECTED  
 IC: INTERNALLY CONNECTED (LOWER)